

# 48503059

# Active-energy meter COUNTIS E02 Direct 40A pulse output + MID



### Strong points

- Compact
- Output (pulses)
- B+D module MID-certified

## General characteristics

- Compact dimensions.
- Measurement accuracy: 1%.
- Displayed on backlit screen.
- Multi-measurement available on display.

# Compliance with standards

- IEC 62053-21 Class 1
- IEC 62053-23 Class 2
- IEC 62053-31
- IEC 62052-11
- EN 50470-1
- EN 50470-3

#### Access to resources (ex: manuals)

2024-05-14 22:07:54



https://www.socomec.co.uk/engb/reference/48503059

COUNTIS E0x devices are modular electrical energy meters, they display kWh and kVArh readings and other measurements on the backlit LCD screen. These devices allow a direct connection up to 40 A.

COUNTIS E02, E04 and E06 units are MID-certified.

NSPSC	41113708
TIM Class	EC001506
GCC	6341
commerce	
ffective date	2019-04-01
ountry of origin	IT
TIM - Electrical characteristics	
ominal current (In) [A]	40
lax. current (Imax) [A]	40
ominal voltage (Un) N-L [V]	184276
requency [Hz]	5060
ccuracy class	В
ole type	Single phase
nergy type	Effective power and blind power
uitable for	Purchase/supply
ariff type	One-tariff
ariff control	External
leasurement type load profile	No
alibrated	Yes
ulse output	Electrical
ulse type	S0
ulse rate [Imp/kWh (kvarh)]	1010
TIM - Mechanical characteristics	
scapement mechanism	No
lounting method	DRA (DIN-rail adapter)
idth in number of modular spacings	1
/ith lock code	No
egree of protection (IP)	IP51
TIM - Technical features	
ype of meter	Electronic
lodel	Direct measurement
pproval	Measuring Instruments Directive
ype of indication	Digital
ype of interface	None
EC40 signature	No
ogistics	
TIN/EAN	3596033073557
	9028301100
ustoms number	
ustoms number rice unit	PC
	PC 0.11
rice unit	

2/024-05-14 22:07:54





Depth of the packing unit	0.105
Norms	
Conformity to standards	IEC
Technical Characteristics	
Application	Metering
Model	E02
Туре	1PH up to 40A, MID

2024-05-14 22:07:54 3/3